



# NC-SAS

## Nurse Calls Staff Assist HELP Station

The Tech Works **NC-SAS** is a call for HELP Station in a semi-flush ABS plastic enclosure for durable emergency signaling. A convenient Push for Help button is provided for activating the Emergency Call directly at the station. Staff is provided with a distinctive "CANCEL" button to reset the station.

An integral call confirmation LED notifies the user that a call has been sent. The Call Assurance Light will be Off if no call is pending, glowing steadily if a Normal Call is pending, and flashing if an Emergency Call is pending.

This is a passive button and light assembly designed for use with active stations like the **NC-DL-12-R** Dome Light. Screw Terminals provide wiring connection to the active electronic stations that provide signaling and control for the **NC-SAS**.

Mounting is a standard 1-gang electrical box. An integral back plate provides mounting and adaptor alignment for the **NC-SAS**.

### BENEFITS

- Reliable Signaling
- No Maintenance
- Low Power
- Simple Wiring
- Easily Integrates to other Systems
- Attractive Station Hardware

### Associated Equipment

**NC-DL-12** Dome Light

### Design Information

**Power** 15V DC  
**Color** White  
**Mounting** 1 Gang Back Box  
**Dimensions** 3.25" W x 0.5" D x 5" H  
**Weight** 0.25 lbs.

### Architects' and Engineers' Specifications

The Nurse Call System Staff Assistance Station shall be a standard one gang electrical box mounting device constructed of ABS plastic. A large Help button shall be included to place a Staff Needs Assistance Call to the System. A distinctive Cancel button shall be provided to reset the station. A call confirmation light shall be included to indicate that a call has been placed. The staff station shall be a passive electronic device requiring no more than 3 mA at 15 Volts DC for full operation.

The Nurse Call System Staff Presence Station shall be Tech Works Model NC-SAS



# Tech Works®

"Making Specialized Communication Easy"



## Quick Start Installation Instructions

